

TRUSTED BATTERY SOLUTIONS










PHR-12500 12V 150.0 AH @ 20-hr. 492 W/Cell @ 15-min.

Rechargeable Sealed Lead Acid Battery PHR - High-Rate Series

TERMINALS: (mm)


Threaded insert with 6mm stud fastener






Torque: 3.9~5.4 Nxm


DIMENSIONS: inch (mm)



13.19 (335) 6.77 (172) 10.83 (275) HT: 10.94 (278)

Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height dimensions. All data subject to change without notice.





CORPORATE HEADOUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020

F: +1 (619) 661 3650

E: customer-service@power-sonic.com

POWER-SONIC EUROPE LIMITED

(EMEA - EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

T: +44 (0)1268 560686

F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

FEATURES

- Superb high-rate discharge characteristics that ensure reliable performance in UPS applications for up to
- · Specifically designed for UPS and critical power backup applications
- Valve regulated, maintenance free spill proof construction
- Precision plate pasting for higher consistency with 100% load testing to ensure uniform capacity
- Patented dual-paste process for enhanced active material bonding and computer guided volumetric electrolyte control for precision filling
- Rugged vibration and impact resistant ABS case and cover flame retardant to UL94-V0

APPROVALS

- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L recognized
- ISO9001:2015 Quality management systems

PERFORMANCE SPECIFICATIONS

Nominal \	V oltage	12 volts (6 cells)					
Nominal I	Power (15 min.)	492 W/Cell					
10-hr.	(7.5A to 10.80 volts) (14.3A to 10.50 volts) (17.5A to 10.50 volts)	150.0 AH 143.0 AH 140.0 AH					
Approxim	ate Weight	92.6 lbs. (42.0 kg)					
Internal R	esistance (approx.)	3.2 milliohms					
Max Disc	harge Current (5 Sec.)	1846 amperes					
Shelf Life 1 Month 3 Month 6 Month	(% of nominal capacity at 68°F (20°C)	97% 91% 83%					
Operating Charge Discharge	Month 83% erating Temperature Range 5°F (-15°C) to 122°F (50°C)						
Case and	Cover	Flame Retardant ABS Plastic UL94:V-0					
Power So	nic Chargers	PSC-1220000-PC					



PHR-12500 12V 150.0 AH @ 20-hr. 492 W/Cell @ 15-min.

Rechargeable Sealed Lead Acid Battery
PHR - High-Rate Series

CONSTANT	CURREN	T DISCH	ARGE (AN	IPERES) A	T 25°C (77°F)									
F.V/Time	5min	10min	15min	20min	30min	45min	1h	2h	3h	4h	5h	6h	8h	10h	20h
1.85V/cell	286	219	182	157	121	89.5	75.4	44.6	34.9	28.4	23.1	20.1	16.2	13.5	7.4
1.80V/cell	383	280	220	186	143	104	84.5	48.7	37.6	30.3	24.8	21.5	17.2	14	7.5
1.75V/cell	432	308	240	200	149	108	88.4	50.5	38.3	31	25.5	22.1	17.5	14.3	7.6
1.70V/cell	476	336	256	210	155	112	91.2	51.8	39.3	31.8	26.1	22.6	17.7	14.6	7.7
1.65V/cell	525	362	272	223	163	115	93.3	52.5	41	32.9	26.9	23.1	18	14.9	7.8
1.60V/cell	579	393	291	238	173	120	94.2	54.8	42.2	33.9	27.8	23.6	18.2	15.1	7.9
CONSTANT	POWER	DISCHAR	GE (WATI	S/CELL)	AT 25°C (77°F)									
F.V/Time	5min	10min	15min	20min	30min	45min	1h	2h	3h	4h	5h	6h	8h	10h	20h
1.85V/cell	497.8	416.3	366.4	329.0	261.1	199.4	162.9	96.6	70.3	56.2	47.3	41.1	32.7	27.3	14.3
1.80V/cell	583.6	464.8	403.5	355.1	278.1	210.8	171.7	100.2	72.9	57.7	48.3	41.8	33.3	27.7	14.6
1.75V/cell	661.2	521.8	438.3	377.7	290.8	219.8	179.2	103.3	75.0	59.3	49.5	42.9	33.9	28.0	14.8
1.70V/cell	722.4	555.3	462.8	397.6	303.2	228.4	185.4	106.7	76.5	60.3	50.4	43.4	34.3	28.3	15.0
1.65V/cell	777.5	591.1	492.0	416.4	317.3	237.7	191.8	109.9	78.2	61.7	51.1	44.1	34.6	28.6	15.2
1.60V/cell	829.6	628.8	511.8	429.8	325.9	242.2	195.1	110.8	78.8	61.9	51.5	44.3	34.6	28.6	15.2

CHARGING

Cycle Applications: Apply constant voltage charge at 2.35v/c - 2.45v/c (14.1 – 14.7v for 12v Monobloc) at 20°C. Initial charging current should be set at less than 0.25C Amps. Switch to float charge to avoid overcharging.

"Float" or "Stand-By" Service: Apply constant voltage charge of 2.25v/c – 2.30v/c (13.5 to 13.8 volts for 12v Monobloc at 20°C. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Temperature Compensation: Charging Voltage for both Cyclic and Standby applications should be regulated in relation to ambient temperature. As temperature rises charging voltage should be reduced to prevent overcharge and increased as temperature falls to avoid undercharge.

For further charging information including temperature compensation factors, see Power Sonic Technical Manual/Power Sonic Charger specifications.

APPLICATIONS

High Rate UPS

Data Centers

To ensure safe and efficient operation always refer to the latest edition of our Technical Manual, as published on our website.

© 2018. Power-Sonic Corporation. All rights reserved. All trademarks are the property of their respective owners.

All data subject to change without notice. E&O.E

CORPORATE HEADQUARTERS (USA AND INTERNATIONAL EXCLUDING EMEA)

Power-Sonic Corporation

7550 Panasonic Way, San Diego, California 92154

T: +1 (619) 661 2020 F: +1 (619) 661 3650

E: customer-service@power-sonic.com

POWER-SONIC EUROPE LIMITED (EMEA – EUROPE, MIDDLE EAST AND AFRICA)

3 Buckingham Square, Hurricane Way, Wickford, Essex SS11 8YQ

T: +44 (0)1268 560686

F: +44 (0)1268 560902

E: salesEMEA@power-sonic.com

CHARGERS

Power Sonic offers a wide range of chargers suitable for batteries with a variety of capacities.

Please refer to our website for more information on our switch mode and transformer type chargers.

Please contact our technical department for advice if you have difficulty in locating a suitable charger.

FURTHER INFORMATION

Please refer to our website www.power-sonic.com for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc.

